

CHAPTER 2

PROBLEM # 2-1

1. $1.4 D = 1.4 (100) = \underline{\hspace{2cm}} 140 \text{ PSF}$

2. $1.2 D + 1.6 L + 0.5 (L_r \text{ or } S \text{ or } R)$
 $1.2(100) + 1.6(70) + 0.5(30) = \underline{\hspace{2cm}} 247 \text{ PSF} \leftarrow$

3. $1.2 D + 1.6 (L_r \text{ or } S \text{ or } R) + (0.5L \text{ or } 0.5W)$
 $1.2(100) + 1.6(30) + 0.5(70) = \underline{\hspace{2cm}} 203 \text{ PSF}$

4. $1.2 D + 1.0 W + 0.5L + 0.5 (L_r \text{ or } S \text{ or } R)$
 $1.2(100) + 1.0(0) + 0.5(70) + 0.5(30) = \underline{\hspace{2cm}} 170 \text{ PSF}$

5. $1.2 D + 1.0 E + 0.5L + 0.2S$
 $1.2(100) + 1.0(0) + 0.5(70) + 0.2(30) = \underline{\hspace{2cm}} 161 \text{ PSF}$

6. $0.9 D + 1.0 W$
 $0.9(100) + 1.0(0) = \underline{\hspace{2cm}} 90 \text{ PSF}$

7. $0.9 D + 1.0 E$
 $0.9(100) + 1.0(0) = \underline{\hspace{2cm}} 90 \text{ PSF}$

GOVERNING FACTORED LOAD = 247 PSF (CASE 2.)

PROBLEM # 2-2

1. $1.4D = 1.4(12000) = \underline{\hspace{10em}} 16,800/lb$

2. DOES NOT CONTROL
(BY INSPECTION)

3. $1.2D + 1.6(L \text{ or } S \text{ or } R) + (0.5L \text{ or } 0.5W)$

$1.2(12,000) + 1.6(\phi) + 0.5(+52,000) = \underline{\hspace{10em}} 40,400/lb$

4. $1.2D + 1.0W + 0.5L + 0.5(L \text{ or } S \text{ or } R)$

$1.2(12,000) + 1.0(52,000) = \underline{\hspace{10em}} 66,400/lb \leftarrow$

5. DOES NOT CONTROL
(BY INSPECTION)

6. $0.9(D) + 1.0W$ (UPLIFT)

$0.9(12,000) + 1.0(-52,000) = \underline{\hspace{10em}} -41,200/lb \leftarrow$

7. DOES NOT CONTROL
(BY INSPECTION)

MAXIMUM FACTORED LOADS:	
+ 66,400 lb	CASE 4,
- 41,200 lb	CASE 6,

SFC ✓

PROBLEM # 2-3

1. $1.4 D = 1.4(9000) = \text{—————} 12,600 \text{ lb}$
2. $1.2 D + 1.6 L + 0.5 (L_r \text{ or } S \text{ or } R)$
 $1.2(9000) + 1.6(5000) + 0.5(2500) = \text{—————} 20,050 \text{ lb} \leftarrow$
3. $1.2 D + 1.6(L_r \text{ or } S \text{ or } R) + (0.5 L \text{ or } 0.5 W)$
 $1.2(9000) + 1.6(2500) + 0.5(5000) = \text{—————} 17,300 \text{ lb}$
4. $1.2 D + 1.0 W + 0.5 L + 0.5(L_r \text{ or } S \text{ or } R)$
 $1.2(9000) + 1.0(\phi) + 0.5(5000) + 0.5(2500) = \text{————} 14,550 \text{ lb}$
5. $1.2 D + 1.0 E + 0.5 L + 0.2 S$
 $1.2(9000) + 1.0(6500) + 0.5(5000) + 0.2(\phi) = \text{—} 19,800 \text{ lb}$
6. ———— DOES NOT CONTROL ————
(BY INSPECTION)
7. $0.9 D + 1.0 E$ (UPLIFT)
 $0.9(9000) + 1.0(-6500) = \text{—————} 1,600 \text{ lb}$

MAXIMUM FACTORED LOADS :

+ 20,050 lb CASE 2

NO UPLIFT

SFC ✓

PROBLEM # 2-4

1. $1.4 D = 1.4 (24) = \underline{\hspace{4cm}} 33.6 \text{ PSF}$

2. $1.2 D + 1.6 L + 0.5 (Lr \text{ or } S \text{ or } R)$
 $1.2(24) + 1.6(\phi) + 0.5(16) = \underline{\hspace{4cm}} 36.8 \text{ PSF}$

3. $1.2 D + 1.6 (Lr \text{ or } S \text{ or } R) + (0.5 L \text{ or } 0.5 W)$
 $1.2(24) + 1.6(16) + 0.5(42) = \underline{\hspace{4cm}} 75.4 \text{ PSF}$

4. $1.2 D + 1.0 W + 0.5 L + 0.5 (Lr \text{ or } S \text{ or } R)$
 $1.2(24) + 1.0(42) + 0.5(0) + 0.5(16) = \underline{\hspace{4cm}} 78.8 \text{ PSF}$

5. DOES NOT CONTROL
(BY INSPECTION)

6. $0.9 D + 1.0 W \text{ (UPLIFT)}$
 $0.9(24) + 1.0(-42) = \underline{\hspace{4cm}} -20.4 \text{ PSF}$

7. DOES NOT CONTROL
(BY INSPECTION)

MAXIMUM FACTORED LOADS :

+ 78.8 PSF CASE 4.

- 20.4 PSF CASE 6.

SFCV

PROBLEM # 2-5

$$D = 64 \text{ PSF} \quad L = 100 \text{ PSF}$$

$$\text{BEAM SPACING} = 7' - 6''$$

$$D(\text{PLF}) = 64(7.5) = 480 \text{ PLF}$$

$$L(\text{PLF}) = 100(7.5) = 750 \text{ PLF}$$

$$1. \quad 1.4 D = 1.4(480) = \underline{\hspace{2cm}} \quad 672 \text{ PLF}$$

$$2. \quad 1.2 D + 1.6 L + 0.5(L_r \text{ or } S \text{ or } R)$$

$$1.2(480) + 1.6(750) = \underline{\hspace{2cm}} \quad 1776 \text{ PLF} \leftarrow$$

$$3. \quad 1.2 D + 1.6(L_r \text{ or } S \text{ or } R) + (0.5L \text{ or } 0.5W)$$

$$1.2(480) + 0.5(750) = \underline{\hspace{2cm}} \quad 951 \text{ PLF}$$

$$4. \quad 1.2 D + 1.0 W + 0.5 L + 0.5(L_r \text{ or } S \text{ or } R)$$

$$1.2(480) + 0.5(750) = \underline{\hspace{2cm}} \quad 951 \text{ PLF}$$

$$5. \quad 1.2 D + 1.0 E + 0.5 L + 0.2 S$$

$$1.2(480) + 0.5(750) = \underline{\hspace{2cm}} \quad 951 \text{ PLF}$$

$$6. \quad 0.9 D + 1.0 W \quad (\text{NO UPLIFT})$$

$$0.9(480) = \underline{\hspace{2cm}} \quad 432 \text{ PLF}$$

$$7. \quad 0.9 D + 1.0 E \quad (\text{NO UPLIFT})$$

$$0.9(480) = \underline{\hspace{2cm}} \quad 432 \text{ PLF}$$

MAXIMUM FACTORED LOAD = 1776 PLF CASE 2.

SFCV ✓

PROBLEM # 2-6

$$D = 20 \text{ PSF} \quad S = 12 \text{ PSF}, L_v = 18 \text{ PSF}, W = 38 \text{ PSF} \uparrow (-)$$
$$16 \text{ PSF} \downarrow (+)$$

$$\text{BEAM SPACING} = 6'-0''$$

$$D \text{ (PLF)} = 20(6) = 120 \text{ PLF}$$

$$S \text{ (PLF)} = 12(6) = 72 \text{ PLF}$$

$$L_v \text{ (PLF)} = 18(6) = 108 \text{ PLF}$$

$$W \text{ (PLF)} = -38(6) = -228 \text{ PLF}$$

$$\text{OR} = +16(6) = 96 \text{ PLF}$$

$$1. \quad 1.4D = 1.4(120) = \underline{\hspace{2cm}} 168 \text{ PLF}$$

$$2. \quad 1.2D + 1.6L + 0.5(L_v \text{ or } S \text{ or } R)$$
$$1.2(120) + 0.5(108) = \underline{\hspace{2cm}} 198 \text{ PLF}$$

$$3. \quad 1.2D + 1.6(L_v \text{ or } S \text{ or } R) + (0.5L \text{ or } 0.5W)$$
$$1.2(120) + 1.6(108) + 0.5(96) = \underline{\hspace{2cm}} 364.8 \text{ PLF} \leftarrow$$

$$4. \quad 1.2D + 1.0W + 0.5L + 0.5(L_v \text{ or } S \text{ or } R)$$
$$1.2(120) + 1.0(96) + 0.5(108) = \underline{\hspace{2cm}} 294 \text{ PLF}$$

$$5. \quad 1.2D + 1.0E + 0.5L + 0.2S$$
$$1.2(120) + 0.2(72) = \underline{\hspace{2cm}} 158.4 \text{ PLF}$$

$$6. \quad 0.9D + 1.0W \text{ (UPLIFT)}$$
$$0.9(120) + 1.0(-228) = \underline{\hspace{2cm}} -120.0 \text{ PLF}$$

7. DOES NOT CONTROL - BY INSPECTION \leftarrow

MAXIMUM FACTORED LOADS:

364.8 PLF CASE 3. DOWNWARD
-120.0 PLF CASE 6. UPWARD

SFCV

2-6

PROBLEM # 2-7

1. $D = 100 = \underline{\hspace{10em}} 100 \text{ PSF}$

2. $D + L = 100 + 70 = \underline{\hspace{10em}} 170 \text{ PSF}$

3. $D + (L_r \text{ or } S \text{ or } R) = 100 + 30 = \underline{\hspace{10em}} 130 \text{ PSF}$

4. $D + 0.75(L) + 0.75(L_r \text{ or } S \text{ or } R)$
 $100 + 0.75(70) + 0.75(30) = \underline{\hspace{10em}} 175 \text{ PSF} \leftarrow$

5. $D + (0.6W \text{ or } 0.7E) = 100 + 0 = \underline{\hspace{10em}} 100 \text{ PSF}$

6a. $D + 0.75L + 0.75(0.6W) + 0.75(L_r \text{ or } S \text{ or } R)$
 $100 + 0.75(70) + 0 + 0.75(30) = \underline{\hspace{10em}} 175 \text{ PSF}$

6b. $D + 0.75L + 0.75(0.7E) + 0.75(S)$
 $100 + 0.75(70) + 0 + 0.75(30) = \underline{\hspace{10em}} 175 \text{ PSF}$

7. $0.6D + 0.6W$ (UPLIFT)
 $0.6(100) + 0 = \underline{\hspace{10em}} 60 \text{ PSF (NO UPLIFT)}$

8. $0.6D + 0.7E$ (UPLIFT)
 $0.6(100) + 0 = \underline{\hspace{10em}} 60 \text{ PSF (NO UPLIFT)}$

GOVERNING LOAD = 175 PSF CASE 4.

SFC ✓

PROBLEM # 2-8

1. $D = 12000 = \underline{\hspace{10em}} 12,000 \text{ lb}$

2. $D + L = 12,000 = \underline{\hspace{10em}} 12,000 \text{ lb}$

3. $D + (L \text{ or } S \text{ or } R) = 12,000 = \underline{\hspace{10em}} 12,000 \text{ lb}$

4. $D + 0.75L + 0.75(L \text{ or } S \text{ or } R)$
 $12,000 = \underline{\hspace{10em}} 12,000 \text{ lb}$

5. $D + (0.6W \text{ or } 0.7E)$
 $12,000 + 0.6(52,000) = \underline{\hspace{10em}} 43,200 \text{ lb} \leftarrow$

6a. $D + 0.75L + 0.75(0.6W) + 0.75(L \text{ or } S \text{ or } R)$
 $12,000 + 0 + 0.75(0.6)52,000 + 0 = \underline{\hspace{10em}} 35,400 \text{ lb}$

6b. $D + 0.75L + 0.75(0.7E) + 0.75(S)$
 $12,000 + 0 = \underline{\hspace{10em}} 12,000 \text{ lb}$

7. $0.6D + 0.6W$ (UPLIFT)
 $0.6(12,000) + 0.6(-52,000) = \underline{\hspace{10em}} -24,000 \text{ lb}$
(UPLIFT)

8. $0.6D + 0.7E$
 $0.6(12,000) + 0 = \underline{\hspace{10em}} 7,200 \text{ lb}$
(NO UPLIFT)

GOVERNING LOADS:	
+ 43,200 lb	CASE 5.
- 24,000 lb	CASE 7.

SFC ✓

PROBLEM # 2-9

1. $D = 9000 = \underline{\hspace{10em}} 9,000 \text{ lb}$

2. $D + L = 9000 + 5000 = \underline{\hspace{10em}} 14,000 \text{ lb}$

3. $D + (L_r \text{ or } S \text{ or } R) = 9000 + 2500 = \underline{\hspace{10em}} 11,500 \text{ lb}$

4. $D + 0.75L + 0.75(L_r \text{ or } S \text{ or } R)$
 $9000 + 0.75(5000) + 0.75(2500) = \underline{\hspace{10em}} 14,625 \text{ lb}$

5. $D + (0.6W \text{ or } 0.7E)$
 $9000 + 0.7(6500) = \underline{\hspace{10em}} 13,550 \text{ lb}$

6a. $D + 0.75L + 0.75(0.6W) + 0.75(L_r \text{ or } S \text{ or } R)$
 $9000 + 0.75(5000) + 0.75(2500) = \underline{\hspace{10em}} 14,625 \text{ lb}$

6b. $D + 0.75L + 0.75(0.7E) + 0.75(L_r \text{ or } S \text{ or } R)$
 $9000 + 0.75(5000) + 0.75(0.7)(6500) + 0.75(2500) = 18,037.5 \text{ lb} \leftarrow$

7. $0.6D + 0.6W$ UPLIFT
 $0.6(9000) + 0 = \underline{\hspace{10em}} 5,400 \text{ lb (No UPLIFT)}$

8. $0.6D + 0.7E$ UPLIFT
 $0.6(9000) + 0.7(-6500) = \underline{\hspace{10em}} 850 \text{ lb (No UPLIFT)}$

GOVERNING LOADS:
18,037.5 lb CASE 6a.
NO UPLIFT

SFCV

PROBLEM # 2-10

1. $D = 24 = \underline{\hspace{10em}}$ 24 psf
2. $D + L = 24 = \underline{\hspace{10em}}$ 24 psf
3. $D + (L_r \text{ or } S \text{ or } R) = 24 + 16 = \underline{\hspace{10em}}$ 40 psf
4. $D + 0.75L + 0.75(L_r \text{ or } S \text{ or } R)$
 $24 + 0.75(16) = \underline{\hspace{10em}}$ 36 psf
5. $D + (0.6W \text{ or } 0.7E)$
 $24 + 0.6(42) = \underline{\hspace{10em}}$ 49.2 psf
- 6a. $D + 0.75L + 0.75(0.6W) + 0.75(L_r \text{ or } S \text{ or } R)$
 $24 + 0 + 0.75(0.6)(42) + 0.75(16) = \underline{\hspace{10em}}$ 54.9 psf ←
- 6b. $D + 0.75L + 0.75(0.7E) + 0.75(L_r \text{ or } S \text{ or } R)$
 $24 + 0 + 0 + 0.75(16) = \underline{\hspace{10em}}$ 36 psf
7. $0.6D + 0.6W$ UPLIFT
 $0.6(24) + 0.6(-42) = \underline{\hspace{10em}}$ -10.8 psf ←
 UPLIFT
8. $0.6D + 0.7E$ UPLIFT
 $0.6(24) + 0 = \underline{\hspace{10em}}$ 14.4 psf
 (NO UPLIFT)

GOVERNING LOADS:	
54.9 psf	CASE 6a.
-10.8 psf	CASE 7. UPLIFT

SFC ✓

PROBLEM # 2-11

$$D = 64 \text{ psf} \quad L = 100 \text{ psf}$$

$$\text{BEAM SPACING} = 7.5 \text{ ft}$$

$$D (\text{PLF}) = 64(7.5) = 480 \text{ PLF}$$

$$L (\text{PLF}) = 100(7.5) = 750 \text{ PLF}$$

1. $D = 480 = \underline{\hspace{10em}} 480 \text{ PLF}$
2. $D + L = 480 + 750 = \underline{\hspace{10em}} 1230 \text{ PLF} \leftarrow$
3. $D + (L \text{ or } S \text{ or } R) = 480 = \underline{\hspace{10em}} 480 \text{ PLF}$
4. $D + 0.75L + 0.75(L \text{ or } S \text{ or } R)$
 $480 + 0.75(750) = \underline{\hspace{10em}} 1042.5 \text{ PLF}$
5. $D + (0.6W \text{ or } 0.7E) = 480 = \underline{\hspace{10em}} 480 \text{ PLF}$
- 6a. $D + 0.75L + 0.75(0.6W) + 0.75(L \text{ or } S \text{ or } R)$
 $480 + 0.75(750) = \underline{\hspace{10em}} 1042.5 \text{ PLF}$
- 6b. $D + 0.75L + 0.75(0.7E) + 0.75(L \text{ or } S \text{ or } R)$
 $480 + 0.75(750) = \underline{\hspace{10em}} 1042.5 \text{ PLF}$
7. $0.6D + 0.6W$ *UPLIFT*
 $0.6(480) + 0 = \underline{\hspace{10em}} 288 \text{ PLF}$
8. $0.6D + 0.7E$
 $0.6(480) + 0 = \underline{\hspace{10em}} 288 \text{ PLF}$

GOVERNING LOAD:

1230 PLF CASE 2.

SFC ✓

PROBLEM # 2-12

$$D = 20 \text{ psf} \quad S = 12 \text{ psf}, L_r = 18 \text{ psf}, W = 38 \text{ psf} \uparrow (-)$$

$$16 \text{ psf} \downarrow (+)$$

$$\text{BEAM SPACING} = 6'-0''$$

$$D (\text{PLF}) = 20 (6) = 120 \text{ PLF}$$

$$S (\text{PLF}) = 12 (6) = 72 \text{ PLF}$$

$$L_r (\text{PLF}) = 18 (6) = 108 \text{ PLF}$$

$$W (\text{PLF}) = -38 (6) = -228 \text{ PLF}$$

$$+ 16 (6) = 96 \text{ PLF}$$

$$1. D = 120 = \underline{\hspace{10em}} 120 \text{ PLF}$$

$$2. D + L = 120 = \underline{\hspace{10em}} 120 \text{ PLF}$$

$$3. D + (L_r \text{ or } S \text{ or } R) = 120 + 108 = \underline{\hspace{10em}} 228 \text{ PLF}$$

$$4. D + 0.75L + 0.75(L_r \text{ or } S \text{ or } R)$$
$$120 + 0.75(108) = \underline{\hspace{10em}} 201 \text{ PLF}$$

$$5. D + (0.6W \text{ or } 0.7E)$$
$$120 + 0.6(96) = \underline{\hspace{10em}} 177.6 \text{ PLF}$$

$$6a. D + 0.75L + 0.75(0.6W) + 0.75(L_r \text{ or } S \text{ or } R)$$
$$120 + 0 + 0.75(0.6)(96) + 0.75(108) = \underline{\hspace{10em}} 244.2 \text{ PLF} \leftarrow$$

$$6b. D + 0.75L + 0.75(0.7E) + 0.75(L_r \text{ or } S \text{ or } R)$$
$$120 + 0 + 0 + 0.75(108) = \underline{\hspace{10em}} 201 \text{ PLF}$$

$$7. 0.6D + 0.6W \quad \text{UPLIFT}$$
$$0.6(120) + 0.6(-228) = \underline{\hspace{10em}} -64.8 \text{ PLF}$$

UPLIFT

GOVERNING LOADS:

244.2 PLF CASE 6a.

-64.8 PLF CASE 7. UPLIFT

SFC ✓

8. — DOES NOT CONTROL (by Inspection) —

2-12